

## SRxxx-K: Cushion Hanger Kits



### **Features:**

- Cushion Inserts measure 3-3/8" diameter by 1" thick and are cut to allow them to be opened for easy cable installation
- Kits include five Cushion Inserts, five Hose Clamps, and five CLH Clamp Heads
- Available for most commonly used cable sizes
- Multiple-hole versions are available for smaller cable sizes
- Clamp Heads have mounting holes for 3/8" hardware and 5/8" slots for use with 1/2" Banding or Hose Clamps up to 9/16"
- Can also be mounted to a 3/4" snap-in hole when used with the SHM-10 Cushion Hanger Snap-In

*We also carry cushion inserts for less commonly used cables and other hole combinations, contact us for additional information*

### **Construction:**

- Inserts are molded from UV-resistant EPDM Rubber for long-term outdoor durability
- Hose Clamps and Clamp Heads are stainless steel

### **Related Products:**

- Can be used outdoors or indoors

## SRxxx-K: Cushion Hanger Kits

### Coax Cables

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SR14F-K	1/4" Flex Coax	0.295"	1	5 pack
SR143F-K	1/4" Flex Coax	0.295"	3	5 pack
SR38-K	3/8" Coax	0.440"	1	5 pack
SR384-K	3/8" Coax	0.440"	4	5 pack
SR123AIR-K	1/2" Air Coax	0.580"	3	5 pack
SR12FLX-K	1/2" Flex Coax	0.520"	1	5 pack
SR123FLX-K	1/2" Flex Coax	0.520"	3	5 pack
SR124FLX-K	1/2" Flex Coax	0.520"	4	5 pack
SR12-K	1/2" Foam Coax	0.630"	1	5 pack
SR122-K	1/2" Foam Coax	0.630"	2	5 pack
SR123-K	1/2" Foam Coax	0.630"	3	5 pack
SR124-K	1/2" Foam Coax	0.630"	4	5 pack
SR129-K	1/2" Foam Coax	0.630"	9	5 pack
SRLR94-K	5/8" Coax	0.870"	4	5 pack
SR78-K	7/8" Coax	1.110"	1	5 pack
SR782-K	7/8" Coax	1.110"	2	5 pack
SR783-K	7/8" Coax	1.110"	3	5 pack
SR784-K	7/8" Coax	1.110"	4	5 pack
SR114-K	1-1/4" Coax	1.560"	1	5 pack
SR158-K	1-5/8" Coax	2.000"	1	5 pack
SR214-K	2-1/4" Coax	2.375"	1	5 pack
SRZERO-K	Blank, No Holes	N/A	0	5 pack

### Mixed Coax

Part #	Cable Size & Type	Hole Sizes	# of Holes	U of M
SR121M-K	(1) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	3	5 pack
SR122M-K	(2) 1/2" Foam Coax & (1) 7/8" Coax	0.63", 1.11"	3	5 pack
SR123M-K	(3) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	5	5pack
SR158M-K	(1) 1/2" foam Coax & (1) 1-5/8" Coax	0.63", 2.0"	2	5pack

## SRxxx-K: Cushion Hanger Kits

### LMR Cables

Part #	Cable Size & Type	Holes Size	# of Holes	U of M
SRLR24-K	LMR-240	0.240"	4	5 pack
SRLX4-K	LMR-400, 3/8" Flex, & RG11U	0.405"	1	5 pack
SRLR42-K	LMR-400, 3/8" Flex, & RG11U	0.405"	2	5 pack
SRLR44-K	LMR-400, 3/8" Flex, & RG11U	0.405"	4	5 pack
SRLR9-K	LMR-900	0.870"	1	5 pack
SRLR94-K	LMR-900	0.870"	4	5 pack

### Elliptical Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SREW43-K	EW43	2.85" x 1.64"	1	5 pack
SREW52-K	EW52, EWP52, & WE61	2.25" x 1.30"	1	5 pack
SREW60-K	WE60	2.10" x 1.15"	1	5 pack
SREW63-K	EW63, EWP63, & WE65	2.01" x 1.165"	1	5 pack
SREW632-K	EW63, EWP63, & WE65	2.01" x 1.165"	2	5 pack
SREW64-K	EW64, EWP64, & WE70	1.92" x 1.12"	1	5 pack
SREW77-K	EW77 & EWP77	1.76" x 1.04"	1	5 pack
SREW85-K	EW85 & WE108	1.33" x 0.92"	1	5 pack
SREW90-K	EW90 & EWP90	1.32" x 0.80"	1	5 pack
SREW903-K	EW90 & EWP90	1.32" x 0.80"	3	5 pack
SREW180-K	EW180, EWP180, WE190, & WE191	0.80" x 0.49"	1	5 pack

### Rectangular Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SRWR75-K	WR75	0.85" x 0.475"	1	5 pack
SRWR90F-K	WR90 Flex	1.21" x 0.67"	1	5 pack
SRWR137-K	WR137	1.50" x 0.75"	1	5 pack
SRWR137F-K	WR137 Flex	1.77" x 1.01"	1	5 pack

### Conduit

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SR34-K	3/4" Conduit	0.77"	1	5 pack