

SRxxx: Cushion Inserts



Features:

- Cushion Inserts measure 3-3/8" diameter by 1" thick and are cut to allow them to be opened for easy cable installation
- Sold individually for use with our B400, B450, and B500 Boot Assemblies
- Available for most commonly used cable sizes
- Multiple-hole versions are available for smaller cable sizes

We also carry cushion inserts for less commonly used cables and other hole combinations, contact us for additional information

Construction:

- Molded from UV-resistant EPDM Rubber for long-term outdoor durability

Design Criteria:

- Can be used outdoors or indoors

SRxxx: Cushion Inserts

Coax Cables

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SR14F	1/4" Flex Coax	0.295"	1	Each
SR143F	1/4" Flex Coax	0.295"	3	Each
SR38	3/8" Coax	0.440"	1	Each
SR384	3/8" Coax	0.440"	4	Each
SR123AIR	1/2" Air Coax	0.580"	3	Each
SR12FLX	1/2" Flex Coax	0.520"	1	Each
SR123FLX	1/2" Flex Coax	0.520"	3	Each
SR124FLX	1/2" Flex Coax	0.520"	4	Each
SR12	1/2" Foam Coax	0.630"	1	Each
SR122	1/2" Foam Coax	0.630"	2	Each
SR123	1/2" Foam Coax	0.630"	3	Each
SR124	1/2" Foam Coax	0.630"	4	Each
SR129	1/2" Foam Coax	0.630"	9	Each
SRLR94	5/8" Coax	0.870"	4	Each
SR78	7/8" Coax	1.110"	1	Each
SR782	7/8" Coax	1.110"	2	Each
SR783	7/8" Coax	1.110"	3	Each
SR784	7/8" Coax	1.110"	4	Each
SR114	1-1/4" Coax	1.560"	1	Each
SR158	1-5/8" Coax	2.000"	1	Each
SR214	2-1/4" Coax	2.375"	1	Each
SRZERO	Blank, No Holes	N/A	0	Each

Mixed Coax

Part #	Cable Size & Type	Hole Sizes	# of Holes	U of M
SR121M	(1) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	3	Each
SR122M	(2) 1/2" Foam Coax & (1) 7/8" Coax	0.63", 1.11"	3	Each
SR123M	(3) 1/2" Foam Coax & (2) 7/8" Coax	0.63", 1.11"	5	Each
SR158M	(1) 1/2" foam Coax & (1) 1-5/8" Coax	0.63", 2.0"	2	Each

SRxxx: Cushion Inserts

LMR Cables

Part #	Cable Size & Type	Holes Size	# of Holes	U of M
SRLR24	LMR-240	0.240"	4	Each
SRLX4	LMR-400, 3/8" Flex, & RG11U	0.405"	1	Each
SRLR42	LMR-400, 3/8" Flex, & RG11U	0.405"	2	Each
SRLR44	LMR-400, 3/8" Flex, & RG11U	0.405"	4	Each
SRLR9	LMR-900	0.870"	1	Each
SRLR94	LMR-900	0.870"	4	Each

Elliptical Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SREW43	EW43	2.85" x 1.64"	1	Each
SREW52	EW52, EWP52, & WE61	2.25" x 1.30"	1	Each
SREW60	WE60	2.10" x 1.15"	1	Each
SREW63	EW63, EWP63, & WE65	2.01" x 1.165"	1	Each
SREW632	EW63, EWP63, & WE65	2.01" x 1.165"	2	Each
SREW64	EW64, EWP64, & WE70	1.92" x 1.12"	1	Each
SREW77	EW77 & EWP77	1.76" x 1.04"	1	Each
SREW85	EW85 & WE108	1.33" x 0.92"	1	Each
SREW90	EW90 & EWP90	1.32" x 0.80"	1	Each
SREW903	EW90 & EWP90	1.32" x 0.80"	3	Each
SREW180	EW180, EWP180, WE190, & WE191	0.80" x 0.49"	1	Each

Rectangular Waveguide

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SRWR75	WR75	0.85" x 0.475"	1	Each
SRWR90F	WR90 Flex	1.21" x 0.67"	1	Each
SRWR137	WR137	1.50" x 0.75"	1	Each
SRWR137F	WR137 Flex	1.77" x 1.01"	1	Each

Conduit

Part #	Cable Size & Type	Hole Size	# of Holes	U of M
SR34	3/4" Conduit	0.77"	1	Each