

SRxxx: Cushion Inserts



A valmont  COMPANY



Features:

- Cushion Inserts measure 3-3/8" diameter by 1" thick and are cut to allow them to be opened for easy cable installation
- Sold individually for use with our B400, B450, and B500 Boot Assemblies
- Available for most commonly used cable sizes
- Multiple-hole versions are available for smaller cable sizes

We also carry cushion inserts for less commonly used cables and other hole combinations, contact us for additional information

Construction:

- Molded from UV-resistant EPDM Rubber for long-term outdoor durability

Design Criteria:

- 4" Boots, 4-1/2" Boots, 5" Boots

created on: 06/19/2023

SRxxx: Cushion Inserts



A valmont COMPANY

Coax Cables

| Part # | Cable Size & Type | Hole Size | # of Holes | U of M |
|----------|-------------------|-----------|------------|--------|
| SR143F | 1/4" Flex Coax | 0.295" | 3 | Each |
| SR38 | 3/8" Coax | 0.440" | 1 | Each |
| SR384 | 3/8" Coax | 0.440" | 4 | Each |
| SR12FLX | 1/2" Flex Coax | 0.520" | 1 | Each |
| SR124FLX | 1/2" Flex Coax | 0.520" | 4 | Each |
| SR12 | 1/2" Foam Coax | 0.630" | 1 | Each |
| SR122 | 1/2" Foam Coax | 0.630" | 2 | Each |
| SR123 | 1/2" Foam Coax | 0.630" | 3 | Each |
| SR124 | 1/2" Foam Coax | 0.630" | 4 | Each |
| SR129 | 1/2" Foam Coax | 0.630" | 9 | Each |
| SRLR94 | 5/8" Coax | 0.870" | 4 | Each |
| SR78 | 7/8" Coax | 1.110" | 1 | Each |
| SR782 | 7/8" Coax | 1.110" | 2 | Each |
| SR783 | 7/8" Coax | 1.110" | 3 | Each |
| SR784 | 7/8" Coax | 1.110" | 4 | Each |
| SR114 | 1-1/4" Coax | 1.560" | 1 | Each |
| SR158 | 1-5/8" Coax | 2.000" | 1 | Each |
| SR214 | 2-1/4" Coax | 2.375" | 1 | Each |
| SRZERO | Blank, No Holes | N/A | 0 | Each |

Mixed Coax

| Part # | Cable Size & Type | Hole Sizes | # of Holes | U of M |
|--------|------------------------------------|--------------|------------|--------|
| SR121M | (1) 1/2" Foam Coax & (2) 7/8" Coax | 0.63", 1.11" | 3 | Each |
| SR122M | (2) 1/2" Foam Coax & (1) 7/8" Coax | 0.63", 1.11" | 3 | Each |
| SR123M | (3) 1/2" Foam Coax & (2) 7/8" Coax | 0.63", 1.11" | 5 | Each |

SRxxx: Cushion Inserts



A valmont COMPANY

LMR Cables

| Part # | Cable Size & Type | Holes Size | # of Holes | U of M |
|--------|-----------------------------|------------|------------|--------|
| SRLR24 | LMR-240 | 0.240" | 4 | Each |
| SRLX4 | LMR-400, 3/8" Flex, & RG11U | 0.405" | 1 | Each |
| SRLR42 | LMR-400, 3/8" Flex, & RG11U | 0.405" | 2 | Each |
| SRLR44 | LMR-400, 3/8" Flex, & RG11U | 0.405" | 4 | Each |
| SRLR94 | LMR-900 | 0.870" | 4 | Each |

Elliptical Waveguide

| Part # | Cable Size & Type | Hole Size | # of Holes | U of M |
|---------|-------------------------------|----------------|------------|--------|
| SREW43 | EW43 | 2.85" x 1.64" | 1 | Each |
| SREW52 | EW52, EWP52, & WE61 | 2.25" x 1.30" | 1 | Each |
| SREW63 | EW63, EWP63, & WE65 | 2.01" x 1.165" | 1 | Each |
| SREW632 | EW63, EWP63, & WE65 | 2.01" x 1.165" | 2 | Each |
| SREW77 | EW77 & EWP77 | 1.76" x 1.04" | 1 | Each |
| SREW772 | EW77 & EWP77 | 1.76" x 1.04" | 2 | Each |
| SREW90 | EW90 & EWP90 | 1.32" x 0.80" | 1 | Each |
| SREW903 | EW90 & EWP90 | 1.32" x 0.80" | 3 | Each |
| SREW180 | EW180, EWP180, WE190, & WE191 | 0.80" x 0.49" | 1 | Each |

Rectangular Waveguide

| Part # | Cable Size & Type | Hole Size | # of Holes | U of M |
|----------|-------------------|----------------|------------|--------|
| SRWR75 | WR75 | 0.85" x 0.475" | 1 | Each |
| SRWR90F | WR90 Flex | 1.21" x 0.67" | 1 | Each |
| SRWR137 | WR137 | 1.50" x 0.75" | 1 | Each |
| SRWR137F | WR137 Flex | 1.77" x 1.01" | 1 | Each |